

RECEIVED
CENTRAL FAX CENTER

SEP 26 2006

Amendments to the claims:

1. (Currently amended) An associative memory device, comprising:
 - an input device for accepting a set or a plurality of sets of input information;
 - one or a plurality of input buffers;
 - the input device being coupled to, or integrated into, the input buffer;
 - a means for transporting the input information to the input buffer;
 - the input buffer being adapted to transform the input information into corresponding sets of complex-valued wave fields as wave-modeled input data;
 - one or a plurality of recording structures, referred to as a cortex;
 - the input buffer being further adapted to propagate the wave-modeled input data to the cortex;
 - the cortex being adapted to associate the desired sets of wave-modeled input data through an invertible mathematical function or operation, thus creating one or a plurality of associations within the cortex;
 - the cortex being further adapted to store the associations in a distributed manner across a cortex surface with other previously stored associations;
 - the cortex being further adapted to form and store ~~arbitrary~~ linear combinations of associations;
 - an input device being operable to accept one or a plurality of retrieval prompts, referred to as a prompt;
 - the input buffer being operable to transform the prompt into a corresponding set of complex-valued wave fields, as a wave-modeled prompt;
 - the input buffer being operable to propagate the wave-modeled prompt to the cortex;
 - the cortex being operable to cause the wave-modeled prompt to mathematically operate upon the previously stored associations using a de-association operation that is the inverse of that originally used to form the associations;
 - the cortex being adapted to store the wave-modeled prompt with other previously stored associations and wave modeled prompts;

a means for the result of the mathematical de-association operation, representing a wave-modeled retrieval, to propagate from the cortex to one or a plurality of output buffers, said output buffer being referred to with the input buffer as the buffers;

the output buffer being operable to transform the wave-modeled retrieval into output data;
and

a means for using control data to provide overall control of the associative memory device.

2. (Previously presented) The associative memory device of Claim 1, wherein the input device further comprises a module for pre-processing the input information.

3. (Previously presented) The associative memory device of Claim 2, wherein the pre-processing module is adapted to assign phase information to the input information.

4. (Previously presented) The associative memory device of Claim 1, further comprising a module for performing post-processing on the wave-modeled retrieval or output data.

5. (Previously presented) The associative memory device of Claim 1, further comprising a means for exporting the wave-modeled retrieval or output data to one or more output devices.

6. (Previously presented) The associative memory device of Claim 1, further comprising a means for retaining input information, wave-modeled input data, prompts, wave modeled prompts, wave modeled retrieval and output data in a volatile memory structure.

7. (Previously presented) The associative memory device of Claim 1, further comprising a means for processing the input information, wave-modeled input data, prompt, wave-modeled prompt, wave-modeled retrieval, output data or control data.

8. (Previously presented) The associative memory device of Claim 1 further comprising a permanent storage device for saving the input information, wave-modeled input data, prompt, wave-modeled prompt, wave-modeled retrieval, output data or control data.

9. (Previously presented) The associative memory device of Claim 1, wherein physical or electronic stimuli comprise the input information.

10. (Previously presented) The associative memory device of Claim 9, wherein the physical or electronic stimuli that are processed further comprises images, fingerprints, signatures, faces, sounds, gas molecules, liquids or chemical compositions.

11. (Previously presented) The associative memory device of Claim 9, wherein a sensor or plurality of sensors are operable to accept the physical or electronic stimuli.

12. (Previously presented) The associative memory device of Claim 11, wherein the sensors further comprise a camera, scanner, keyboard, computer, mouse, analog recorder, digital recorder, odor detector, digital signature capture apparatus, or microphone.

13. (Previously presented) The associative memory device of Claim 1, wherein the input buffer is operable to:

- transform input information into corresponding sets of complex-valued wave fields;
- transform prompts into corresponding sets of complex-valued wave fields;
- propagate wave-modeled input data to the cortex; and
- propagate wave-modeled prompts to the cortex.

14. (Previously presented) The associative memory device of Claim 1, wherein output buffer is operable to:

- accept the wave-modeled retrieval propagated from the cortex;
- transform the wave-modeled retrieval from a complex-valued wave fields to a data format.

15. (Previously presented) The associative memory device of Claim 1, wherein the input buffer and the output buffer further comprise a single buffer unit adapted to operate in either an input mode, an output mode, or both simultaneously.

16. (Currently amended) The associative memory device of Claim 1, wherein the cortex further comprises a plurality of interconnected modules to perform associated memory operations further comprising:

- a module to receive and store sets of complex-valued wave fields propagated from the input buffer;

- a second module to form and store associations with propagated wave fields using an invertible mathematical operation;

- a module to form and store ~~arbitrary~~ linear combinations of associations;

- a module to receive a wave-modeled prompt;

- a module to mathematically operate upon the previously stored associations using a de-association function that is the inverse of that originally used to form the associations;

- a module to generate the complex conjugate of the de-associated wave fields; and

- a module to propagate the results of the operation to the output buffer.

17. (Previously presented) The associative memory device of Claim 1, wherein the buffers further comprise:

- physical antenna arrays;
- computer hardware which is coupled to the physical antenna arrays; and
- computer software being adapted to program the computer hardware to perform wave modeling, wave propagation, wave reception and wave transformation operations.

18. (Previously presented) The associative memory device of Claim 17, wherein the physical antenna arrays further comprise:

- multiple receiving antennas with corresponding receiver memory elements;
- multiple broadcast antennas with corresponding broadcast memory elements;
- a receiver array controller; and
- a broadcast array controller.

19. (Previously presented) The associative memory device of Claim 17, wherein the computer hardware further comprises;

- an analog-to-digital converter with an input and output;
- a device driver coupled to the input of the analog-to-digital converter;
- a preprocessor module with an input and output;
- the input to the preprocessor module coupled to the output of the analog-to-digital converter;
- a phase assignment module with an input and an output;
- the output of the preprocessor module coupled to an input of the phase assignment module;
- a central processing unit (CPU);
- the CPU having a main buffer memory;
- the output of the phase assignment module being coupled to or integral to the CPU;
- a post-processor module with an input and output; and
- the CPU being coupled to the input of the post-processor module.

20. (Previously presented) The associative memory device of Claim 1, wherein the buffer further comprises:

- computer hardware with an input and output;
- computer software adapted to program the computer hardware;
- a device driver, with an input and an output,

the output of the device driver being coupled to the input of the computer hardware;
an analog-to-digital converter being integral to the computer hardware operable to convert analog input information into digital input information;
a pre-processor module, the pre-processor module being integral to the computer hardware or configured therein with the computer software and being operable to process input information;
a phase assignment module, the phase assignment module being integral to the computer hardware or configured therein with the computer software, and being operable for conditioning the input information into wave-modeled input data;
a post-processor module, the post-processor module being integral to the computer hardware or configured therein with the computer software and being operable to transform the wave-modeled retrieval into output data;
a wave propagation calculation module, the wave propagation calculation module being integral to the computer hardware or configured therein with the computer software and being operable to calculate wave propagation properties;
the computer hardware having a main buffer memory for storing the input information, wave-modeled input data, prompt, wave-modeled prompt, wave-modeled retrieval, output data or control data; and
buffer data arrays comprising both receiver memory elements and broadcast memory elements being integral to the computer hardware.

21. (Previously presented) The associative memory device of Claim 1, wherein the buffers further comprise:

an application-specific integrated circuit (ASIC) or a field programmable gate array (FPGA) with an input and output;
a device driver, with an input and an output,
the output of the device driver being coupled to the input of the ASIC or FPGA;
an analog-to-digital converter being integral or external to the ASIC or FPGA operable to convert analog input information into digital input information,
a pre-processor module, the pre-processor module being integral or external to the ASIC or FPGA and being operable to process input information;

a phase assignment module, the phase assignment module being integral or external to the ASIC or FPGA and being operable to condition the input information into wave-modeled input data;

a post-processor module, the post-processor module being integral or external to the ASIC or FPGA and being operable to transform the wave-modeled retrieval into output data;

a wave propagation calculation module, the wave propagation calculation module being integral or external to the ASIC or FPGA and being operable to calculate wave propagation properties;

the ASIC or FPGA having a main buffer memory for storing the input information, wave-modeled input data, prompt, wave-modeled prompt, wave-modeled retrieval, output data or control data; and

buffer data arrays comprising both receiver memory elements and broadcast memory elements being integral or external to the ASIC or FPGA.

22. (Previously presented) The associative memory device of Claim 1, wherein the buffers further comprise:

an analog computer system utilizing a plurality of operational amplifiers, said analog computer having an input and output;

a device driver, with an input and an output;

the output of the device driver being coupled to the input of the analog computer;

a pre-processor module, the pre-processor module being integral or external to the analog computer and being operable to process input information;

a phase assignment module, the phase assignment module being integral or external to the analog computer and being operable to condition the input information into wave-modeled input data;

a post-processor module, the post-processor module being integral or external to the analog computer and being operable to transform the wave-modeled retrieval into output data;

a wave propagation calculation module, the wave propagation calculation module being integral or external to the analog computer and being operable to calculate wave propagation properties;

the analog computer having a main buffer memory for storing the input information, wave-modeled input data, prompt, wave-modeled prompt, wave-modeled retrieval, output data or control data; and

buffer data arrays comprising both receiver memory elements and broadcast memory elements being integral to the analog computer.

23. (Previously presented) The associative memory device of Claim 1, wherein the cortex further comprises:

a physical antenna array;

a processing unit with an input and output;

the physical antenna array being coupled to the input of the processing unit;

the physical antenna array having a receiver array controller, a broadcast array controller, multiple receiving antennas with corresponding receiver memory elements, one set of receiver memory elements for each buffer element in the associative memory device, and multiple broadcast antennas with corresponding broadcast memory elements;

an association module, the association module being integral to the processing unit;

a de-association module, the de-association module being integral to the processing unit;

a linear combination module, the linear combination module being integral to the processing unit;

a complex conjugation module, the complex conjugation module being integral to the processing unit;

a main cortex memory being integral to the processing unit, the main cortex memory further comprising association memory elements; de-association memory elements; and linear combination memory elements.

24. (Previously presented) The associative memory device of Claim 23, wherein the cortex further comprises:

a wave propagation calculation module, the wave propagation calculation module being integral to the processing unit and being operable to calculate wave propagation properties; and

cortex data arrays comprised of receiver memory elements, one set of receiver memory elements for each buffer in the associative memory system, broadcast memory elements, association memory elements, de-association memory elements, and linear combination memory elements.

25. (Previously presented) The associative memory device of Claim 23, wherein the processing unit further comprises a programmable computer hardware and computer software system, an application-specific integrated circuit (ASIC) or a field programmable gate array (FPGA).

26. (Previously presented) The associative memory device of Claim 23, wherein the processing unit further comprises an analog computer system utilizing a plurality of operational amplifiers.

27. (Previously presented) The associative memory device of Claim 23, wherein the processing unit further comprises a programmable computer hardware and computer software system, an application-specific integrated circuit (ASIC) a field programmable gate array (FPGA) or an analog computer system utilizing a plurality of operational amplifiers.

28. (Currently amended) The associative memory device of Claim 1, wherein the implementation of the associative memory device is mathematically modeled with wave-modeled input data on the buffer being denoted by:

$$P_i, P_j, \dots, P_l;$$

the propagated forms of the wave-modeled input data on the cortex being denoted by:

$$P'_i, P'_j, \dots, P'_l;$$

an association formed from the wave-modeled input data being denoted by:

$$\langle P'_i, P'_j, \dots, P'_l \rangle \equiv f(P'_i, P'_j, \dots, P'_l),$$

in which the association operation is defined by an ~~arbitrary~~, invertible mathematical function f and a ~~an arbitrary~~ linear combination of associations being denoted by:

$$\sum_m \alpha_m \langle P'_{i,m}, P'_{j,m}, \dots, P'_{l,m} \rangle = \sum_m \alpha_m f(P'_{i,m}, P'_{j,m}, \dots, P'_{l,m}),$$

where α_m is a ~~an arbitrary~~ weighting factor for the m^{th} association.

29. (Previously presented) The associative memory device of Claim 28, wherein the association function f corresponds to the mathematical operation of multiplication such that two propagated input patterns $P'_i = \psi_m$ and $P'_j = \phi_m$ are associated by multiplying the complex amplitudes of the two wave functions, point by point, at each location r_C in the cortex, with the association represented mathematically as:

$$\psi_m(r_C) \phi_m(r_C)$$

and with all associations previously stored, C , written as the linear combination of associations:

$$C(r_c) = \sum_m \alpha_m \psi_m(r_c) \phi_m(r_c).$$

30. (Previously presented) The associative memory device of Claim 28, wherein the association function f corresponds to the mathematical operation of multiplication of wave fields, one or more of which may be point-wise normalized, the rest non-normalized, such that two propagated input patterns $P_i = \psi_m$ and $P_j = \phi_m$ are associated by multiplying the point-wise complex amplitudes of the two wave functions, at each location r_c in the cortex with the association represented mathematically as:

$$\exp[i \text{Arg}(\psi(r_c))] \exp[i \text{Arg}(\phi(r_c))]$$

or

$$\psi(r_c) \exp[i \text{Arg}(\phi(r_c))]$$

where $\text{Arg}(z)$ is the phase angle for a complex value z , and with all associations previously stored written as the linear combination of associations:

$$C(r_c) = \sum_m \alpha_m \exp[i \text{Arg}(\psi_m(r_c))] \exp[i \text{Arg}(\phi_m(r_c))]$$

or

$$C(r_c) = \sum_m \alpha_m \psi_m(r_c) \exp[i \text{Arg}(\phi_m(r_c))]$$

31. (Currently amended) The associative memory device of Claim 1, wherein the implementation of the associative memory device is mathematically modeled with the wave-modeled prompt on the input buffer being denoted by:

$$R_i, R_j, \dots, R_l;$$

the respective propagated forms of the wave-modeled prompt on the cortex being denoted by:

$$R'_i, R'_j, \dots, R'_l,$$

the wave-modeled prompt being operable to probe the plurality of previously stored associations using f^{-1} , the inverse of the function used originally to form the associations; and the resulting de-associated wave \bar{D} being denoted by:

$$\bar{D} = \langle C | R'_i, R'_j, \dots, R'_l \rangle = f^{-1}(C | R'_i, R'_j, \dots, R'_l) = f^{-1}(\sum_m \alpha_m f(P_{i,m}, P_{j,m}, \dots, P_{l,m}) | R'_i, R'_j, \dots, R'_l);$$

where α_m is a ~~an arbitrary~~ weighting factor for the m^{th} association, a de-association is denoted by angle brackets with a vertical bar separating the first argument, the entity being probed, from the second argument, the set of one or more prompting fields; and D represents the retrieval formed when the complex conjugate of the de-association (D^*) is propagated from the cortex to the output buffer.

32. (Previously presented) The associative memory device of Claim 31 further comprising multiplication for the association operation, and the inverse function, f^{-1} , division for the retrieval operation, wherein if a wave field ϕ_n is used to probe the previously stored associated pairs in the cortex, then the retrieval process is denoted by:

$$C\phi_n = \sum_m \alpha_m \psi_m \phi_m I\phi_n = \sum_m \alpha_m \psi_m \phi_m \phi_n^{-1} = \alpha_n \psi_n + \sum_{m \neq n} \alpha_m \psi_m \phi_m \phi_n^{-1},$$

further, given that the inverse operator I corresponds to division, the retrieval process is more specifically denoted by:

$$C\phi_n = \sum_m \frac{\alpha_m \psi_m \phi_m}{\phi_n} = \alpha_n \psi_n + \sum_{m \neq n} \frac{\alpha_m \psi_m \phi_m}{\phi_n}$$

where C contains the linear combination of previously stored associations, and, at each point on the cortex r_c on which C is defined, the value of C is divided by the value of ϕ_n , with the retrieval, $\alpha_n \psi_n$, being propagated to the output buffer and then to the output device.

33. (Previously presented) The associative memory device of Claim 30, further comprising:

a retrieval operation, multiplication corresponding to the association operation, using complex conjugation as the inverse function f^{-1} , such that if the point-wise normalized wave field ϕ_n is used to probe the previously stored associated pairs in the cortex;

the probe process being denoted by:

$$\begin{aligned} C\phi_n &= \sum_m \alpha_m \exp[i\text{Arg}(\psi_m)] \exp[i\text{Arg}(\phi_m)] I \exp[i\text{Arg}(\phi_n)] \\ &= \sum_m \alpha_m \exp[i\text{Arg}(\psi_m)] \exp[i\text{Arg}(\phi_m)] \exp[i\text{Arg}(\phi_n)]^{-1} \end{aligned}$$

or

$$C\phi_n = \sum_m \alpha_m \psi_m \exp[i\text{Arg}(\phi_m)] I \exp[i\text{Arg}(\phi_n)] = \sum_m \alpha_m \psi_m \exp[i\text{Arg}(\phi_m)] \exp[i\text{Arg}(\phi_n)]^{-1}$$

further, given that the inverse operator \mathbf{I} , which embodies the inverse function f^{-1} , corresponds to complex conjugation, the probe process more specifically by:

$$\begin{aligned} C\phi_n &= \sum_m \alpha_m \exp[i\text{Arg}(\psi_m)] \exp[i\text{Arg}(\phi_m)] \exp[-i\text{Arg}(\phi_n)] \\ &= \alpha_n \exp[i\text{Arg}(\psi_n)] + \sum_{m \neq n} \alpha_m \exp(i[\text{Arg}(\psi_m) + \text{Arg}(\phi_m) - \text{Arg}(\phi_n)]) \end{aligned}$$

or

$$\begin{aligned} C\phi_n &= \sum_m \alpha_m \psi_m \exp[i\text{Arg}(\phi_m)] \exp[-i\text{Arg}(\phi_n)] \\ &= \alpha_n \psi_n + \sum_{m \neq n} \alpha_m \psi_m \exp(i[\text{Arg}(\phi_m) - \text{Arg}(\phi_n)]) \end{aligned}$$

where \mathbf{C} contains the linear combination of previously stored associations, and, at each point \mathbf{r}_c on the cortex on which \mathbf{C} is defined, the value of \mathbf{C} is multiplied by the complex conjugate of the exponential of the phase angle of the prompt ϕ_n , with the retrieval being propagated to the output buffer and to the output device.

34. (Previously presented) The associative memory device of Claim 1, wherein the means of transport of input information, a prompt and a retrieval is through the propagation of physical waves by antenna arrays and supporting computer hardware and computer software.

35. (Currently amended) The associative memory device of Claim 1, further comprising computer hardware and computer software operable to transport input information, prompt and retrieval through the simulation of wave propagation in which sets of data representing input information, prompt and retrieval are input, pre-processed, and then represented as wave functions $\xi_i(\mathbf{r})$ that are time-harmonic solutions to the wave equation:

$$(\nabla^2 + k^2)\xi_i(\mathbf{r}) = 0;$$

in which the propagation of a wave away from a surface (for example, a buffer or a cortex) is formally and exactly described by the Kirchhoff integral:

$$\xi_i(\mathbf{r}) = \oint_{S_C} dS_C \cdot \{ \xi_i(\mathbf{r}_C) \nabla_C G(\mathbf{r}, \mathbf{r}_C) - G(\mathbf{r}, \mathbf{r}_C) \nabla_C \xi_i(\mathbf{r}_C) \}$$

where the surface S_C is closed and completely surrounds ~~the arbitrary~~ a destination point \mathbf{r} , the gradient operates only on coordinates on the source surface S_C , and $G(\mathbf{r}, \mathbf{r}_C)$ is a Green's function; and in which the above continuous integral is discretized for numerical implementation as:

$$\xi(\mathbf{r}) = \sum_{\text{all source points}} \Delta S_c \cdot \{ \xi(\mathbf{r}_c) \nabla_c G(\mathbf{r}, \mathbf{r}_c) - G(\mathbf{r}, \mathbf{r}_c) \nabla_c \xi(\mathbf{r}_c) \}$$

thus enabling digital input, output, and computation.

36. (Previously presented) The associative memory device of Claim 35, wherein said computer hardware and computer software comprises a combination of hardwired wave propagation circuitry and software running on computer hardware.

37. (Previously presented) The associative memory device of Claim 1, wherein the wave-modeled retrieval and output data corresponds to any of the sets of wave-modeled input data propagated to the cortex and associated with other data.

38. (Currently amended) An associative memory device, comprising:
 one or a plurality of input devices;
 one or a plurality of input buffers;
 one or a plurality of recording structures, referred to as a cortex;
 one or a plurality of output buffers, referred to with the input buffer as the buffers;
 one or a plurality of output devices;
 one or a plurality of overall system controllers;
 one or a plurality of volatile memory units;
 one or a plurality of permanent storage devices, and one or a plurality of processing units;
 the input device operable to sense input information comprising physical or electronic stimuli ~~of arbitrary nature and origin;~~

the input device being coupled to the input buffer and being further operable to transport the input information to the input buffer;

the input buffer operable to transform the input information into corresponding sets of complex-valued wave fields;

the input buffer being further operable to pre-process the input information and assign phase information;

the input buffer being further operable to propagate the sets of complex-valued wave fields representing the input information and referred to as wave-modeled input data to the cortex;

the cortex being operable to accept the wave-modeled input data;

the cortex being adapted to retain the wave-modeled input data from the input buffer in a distributed manner across a cortex surface;

the cortex being further operable to associate the desired sets of wave-modeled input data through an invertible mathematical function or operation, thus creating one or more associations within the cortex;

the cortex being further operable to create and store ~~arbitrary~~ linear combinations of associations;

the input device, when enabled, being further operable to sense additional sets of input information comprising physical or electronic stimuli or other input data to act as a prompt or prompts to make a retrieval or retrievals;

the input buffer being further operable to transform the prompting set of input information into corresponding sets of complex-valued wave fields, referred to as the wave-modeled prompt;

the input buffer being further operable to preprocess the prompting set of input information and assign phase information;

the input information to be retrieved from the cortex comprising any of the sets of physical or electronic stimuli stored in previously created associations, as determined by the operator;

the input buffer, when enabled, being further operable to propagate the wave-modeled prompt to the cortex;

the cortex being operable to accept a probe from the input buffer carried by a wave-modeled prompt using a de-association function or operation that is the inverse of that originally used to form the association;

the cortex being further operable to propagate the results of the de-association, representing a retrieval, to the output buffer;

the output buffer being adapted to receive, post-process, and export the retrieval to one or more output devices in human or machine-readable form.

39. (Previously presented) The associative memory device of Claim 38, the buffer and cortex are operable to generate and propagate wave fronts within the associative memory device.

40. (Previously presented) The associative memory device of Claim 38, wherein a first set of buffers processes images, a second set of buffers processes sounds, a third set of buffers

processes representations of gas molecules and a fourth set of buffers processes chemical compositions.

41. (Previously presented) The associative memory device of Claim 38, wherein the cortex is adapted to store a plurality of sensed physical or electronic data in a distributed manner.

42. (Previously presented) The associative memory device of Claim 38, wherein the input buffer, cortex and output buffer are adapted to receive and process a plurality of sensed physical or electronic stimuli simultaneously.

43. (Previously presented) The associative memory device of Claim 38, adapted to perform autonomous pattern recognition or identification operations.

44. (Currently amended) The associative memory device of Claim 43, further comprising:
an internal identification pattern (IIP) buffer, operable to store unique, machine-readable patterns for autonomous identification purposes;

an IIP generator module, operable to create a unique, machine-readable pattern given a unique identification code chosen automatically or supplied by a system operator;

the IIP generator module, further operable to link each specific IIP to ~~arbitrary~~ sets of information (such as data files) to be recalled, sets of commands to be executed or communicated upon a positive identification, and threshold confidence levels required for execution of each particular command or sets of commands;

an IIP reader module, operable to read autonomously a retrieved pattern and deduce an identification code that corresponds to a previously created IIP;

the IIP reader module further operable to provide a confidence estimate based on relative certainty or uncertainty of its identification;

an autonomous execution module, operable to receive the identification result and confidence estimate from the IIP reader module, to recall the associated files or other information related to the reported identification code, and further to execute or communicate the appropriate commands based on the identification code, the reported confidence estimate, and the predefined confidence levels required for the relevant commands;

an adaptive learning module, operable to modify the plurality of associations stored in the cortex in response to feedback on the accuracy of its identification, so as to improve its recognition

performance, in which the general adaptation process is defined by the following equation for the case of a false positive identification of prompting pattern R_i :

$$C_{new} = C_{old} - \beta_i \langle R_i, I_j \rangle$$

where C_{old} is the original cortex value, C_{new} is the cortex value after adaptive learning, β_i is a positive weighting factor, and I_j is the incorrectly retrieved IIP;

and where the general adaptation process is defined by the following equation for the case of a false negative or overly weak positive identification of prompting pattern R_i :

$$C_{new} = C_{old} + \beta_i \langle R_i - \gamma_i P_i, I_i \rangle$$

where C_{old} is the original cortex value, C_{new} is the cortex value after adaptive learning, β_i is a positive weighting factor, I_i is the desired IIP, P_i is the original pattern associated with I_i , and γ_i is 0 for augmentation mode and 1 for replacement mode.

45. (Previously presented) The associative memory device of Claim 44, further comprising computer hardware and software.

46. (Previously presented) The associative memory device of Claim 44, further comprising one or a plurality of application-specific integrated circuits (ASICs) or field programmable gate arrays (FPGAs).

47. (Previously presented) The associative memory device of Claim 44 further comprising an analog computer system utilizing a plurality of operational amplifiers.

48. (Previously presented) The associative memory device of Claim 44, wherein the pattern recognized is an image, human face, fingerprint, signature, gas molecule, substance, liquid or chemical composition.

49. (Previously presented) The associative memory device of Claim 43, wherein a sensor or plurality of sensors comprise the input device.

50. (Previously presented) The associative memory device of Claim 49, wherein the sensor comprises a film still or moving picture camera, still or moving video camera, scanner, a device to convert gas molecules into signals, or a microphone.

51. (Previously presented) The associative memory device of Claim 50, wherein the device to convert gas molecules into signals comprises directly heated short chromatography columns, cooled sample traps, surface acoustic wave (SAW) interferometric vapor detectors.

52. (Previously presented) The associative memory device of Claim 43, wherein the input data representing physical stimuli comprises analog or discrete electrical signals .

53. (Previously presented) The associative memory device of Claim 43, wherein the means of information transport is through the propagation of physical waves by antenna arrays and supporting hardware and software.

54. (Currently amended) The associative memory device of Claim 43, wherein the means of information transport is through the simulation of wave propagation in computer software operating on computer hardware, in which sets of data are input, pre-processed, and then represented as wave functions $\xi_i(\mathbf{r})$ that are time-harmonic solutions to the wave equation:

$$(\nabla^2 + k^2)\xi_i(\mathbf{r}) = 0;$$

in which the propagation of a wave away from a surface such as a buffer or the cortex is formally and exactly described by the Kirchhoff integral:

$$\xi_i(\mathbf{r}) = \oint_{S_C} dS_C \cdot \{ \xi_i(\mathbf{r}_C) \nabla_C G(\mathbf{r}, \mathbf{r}_C) - G(\mathbf{r}, \mathbf{r}_C) \nabla_C \xi_i(\mathbf{r}_C) \}$$

where the surface S_C is closed and completely surrounds ~~a the arbitrary~~ destination point \mathbf{r} , the gradient operates only on coordinates on the source surface S_C , and $G(\mathbf{r}, \mathbf{r}_C)$ is a Green's function; and in which the above continuous integral is discretized for numerical implementation as

$$\xi(\mathbf{r}) = \sum_{\text{all source points}} \Delta S_C \cdot \{ \xi(\mathbf{r}_C) \nabla_C G(\mathbf{r}, \mathbf{r}_C) - G(\mathbf{r}, \mathbf{r}_C) \nabla_C \xi(\mathbf{r}_C) \}$$

thus enabling digital input, output, and computation.

55. (Previously presented) The associative memory device of Claim 43, wherein said computer hardware and computer software comprises a combination of hardwired wave propagation circuitry and software running on computer hardware.

56. (Previously presented) The associative memory device of Claim 43, wherein the wave-modeled retrieval and output data corresponds to any of the sets of wave-modeled input data propagated to the cortex and associated with other data.

57. (Previously presented) The associative memory device of Claim 43, wherein the buffers further comprise:

physical antenna arrays;

computer hardware which is coupled to the physical antenna arrays; and

computer software being adapted to program the computer hardware to perform wave modeling, wave propagation, wave reception and wave transformation operations.

58. (Previously presented) The associative memory device of Claim 57, wherein the physical antenna arrays further comprise:

- multiple receiving antennas with corresponding receiver memory elements;
- multiple broadcast antennas with corresponding broadcast memory elements;
- a receiver array controller; and
- a broadcast array controller.

59. (Previously presented) The associative memory device of Claim 57, wherein the computer hardware further comprises:

- an analog-to-digital converter with an input and output;
- a device driver coupled to the input of the analog-to-digital converter;
- a preprocessor module with an input and output;
- the input to the preprocessor module coupled to the output of the analog-to-digital converter;
- a phase assignment module with an input and an output;
- the output of the preprocessor module coupled to an input of the phase assignment module;
- a central processing unit (CPU);
- the CPU having a main buffer memory;
- the output of the phase assignment module being coupled to or integral to the CPU;
- a post-processor module with an input and output; and
- the CPU being coupled to the input of the post-processor module.

60. (Previously presented) The buffers of Claim 43, further comprising:

- computer hardware with an input and output;
- computer software adapted to program the computer hardware;
- a device driver, with an input and an output,
- the output of the device driver being coupled to the input of the computer hardware;
- an analog-to-digital converter being integral to the computer hardware operable to convert analog input information into digital input information,
- a pre-processor module, the pre-processor module being integral to the computer hardware or configured therein with the computer software and being operable to process input information;

a phase assignment module, the phase assignment module being integral to the computer hardware or configured therein with the computer software, and being operable for conditioning the input information into wave-modeled input data;

a post-processor module, the post-processor module being integral to the computer hardware or configured therein with the computer software and being operable to transform the wave-modeled retrieval into output data;

a wave propagation calculation module, the wave propagation calculation module being integral to the computer hardware or configured therein with the computer software and being operable to perform wave propagation calculations;

the computer hardware having a main buffer memory for storing the input information, wave-modeled input data, prompt, wave-modeled prompt, wave-modeled retrieval, output data or control data; and

buffer data arrays comprising both receiver memory elements and broadcast memory elements being integral to the computer hardware.

61. (Previously presented) The associative memory device of Claim 43, wherein the buffers further comprise:

an application-specific integrated circuit (ASIC) or a field programmable gate array (FPGA) with an input and output;

a device driver, with an input and an output,

the output of the device driver being coupled to the input of the ASIC or FPGA;

an analog-to-digital converter being integral or external to the ASIC or FPGA operable to convert analog input information into digital input information,

a pre-processor module, the pre-processor module being integral or external to the ASIC or FPGA and being operable to process input information;

a phase assignment module, the phase assignment module being integral or external to the ASIC or FPGA and being operable to condition the input information into wave-modeled input data;

a post-processor module, the post-processor module being integral or external to the ASIC or FPGA and being operable to transform the wave-modeled retrieval into output data;

a wave propagation calculation module, the wave propagation calculation module being integral or external to the ASIC or FPGA and being operable to perform wave propagation calculations;

the ASIC or FPGA having a main buffer memory for storing the input information, wave-modeled input data, prompt, wave-modeled prompt, wave-modeled retrieval, output data or control data; and

buffer data arrays comprising both receiver memory elements and broadcast memory elements being integral or external to the ASIC or FPGA.

62. (Previously presented) The associative memory device of Claim 43, wherein the buffers further comprise:

an analog computer system utilizing a plurality of operational amplifiers, said analog computer having an input and output;

a device driver, with an input and an output;

the output of the device driver being coupled to the input of the analog computer;

a pre-processor module, the pre-processor module being integral or external to the analog computer and being operable to process input information;

a phase assignment module, the phase assignment module being integral or external to the analog computer and being operable to condition the input information into wave-modeled input data;

a post-processor module, the post-processor module being integral or external to the analog computer and being operable to transform the wave-modeled retrieval into output data;

a wave propagation calculation module, the wave propagation calculation module being integral or external to the analog computer and being operable to perform wave propagation calculations;

the analog computer having a main buffer memory for storing the input information, wave-modeled input data, prompt, wave-modeled prompt, wave-modeled retrieval, output data or control data; and

buffer data arrays comprising both receiver memory elements and broadcast memory elements being integral to the analog computer.

63. (Previously presented) The cortex of Claim 43, further comprising:

a physical antenna array;
a processing unit with an input and output;
the physical antenna array being coupled to the input of the processing unit;
the physical antenna array having a receiver array controller, a broadcast array controller, multiple receiving antennas with corresponding receiver memory elements, one set of receiver memory elements for each buffer element in the associative memory device, and multiple broadcast antennas with corresponding broadcast memory elements;
an association module, the association module being integral to the processing unit;
a de-association module, the de-association module being integral to the processing unit;
a linear combination module, the linear combination module being integral to the processing unit;
a complex conjugation module, the complex conjugation module being integral to the processing unit;
a main cortex memory being integral to the processing unit, the main cortex memory further comprising association memory elements; de-association memory elements; and linear combination memory elements.

64. (Previously presented) The associative memory device of Claim 63, wherein the cortex further comprises:

a wave propagation calculation module, the wave propagation calculation module being integral to the processing unit and being operable to perform wave propagation calculations; and
cortex data arrays comprised of receiver memory elements, one set of receiver memory elements for each buffer in the associative memory system, broadcast memory elements, association memory elements, de-association memory elements, and linear combination memory elements.

65. (Previously presented) The associative memory device of Claim 64, wherein the processing unit further comprises a programmable computer hardware and computer software system, an application-specific integrated circuit (ASIC) or a field programmable gate array (FPGA).

66. (Previously presented) The associative memory device of Claim 64, wherein the processing unit further comprises an analog computer system utilizing a plurality of operational amplifiers.

67. (Previously presented) The associative memory device of Claim 64, wherein the processing unit further comprises a programmable computer hardware and computer software system, an application-specific integrated circuit (ASIC) a field programmable gate array (FPGA) or an analog computer system utilizing a plurality of operational amplifiers.

68. (Currently amended) The associative memory device of Claim 43, wherein the implementation of the associative memory device is mathematically modeled with wave-modeled input data on the buffer being denoted by:

$$P_i, P_j, \dots, P_l;$$

the propagated forms of the wave-modeled input data on the cortex being denoted by:

$$P'_i, P'_j, \dots, P'_l;$$

an association formed from the wave-modeled input data being denoted by:

$$\langle P'_i, P'_j, \dots, P'_l \rangle \equiv f(P'_i, P'_j, \dots, P'_l),$$

in which the association operation is defined by an **arbitrary**, invertible mathematical function f and a **an-arbitrary** linear combination of associations being denoted by:

$$\sum_m \alpha_m \langle P'_{i,m}, P'_{j,m}, \dots, P'_{l,m} \rangle = \sum_m \alpha_m f(P'_{i,m}, P'_{j,m}, \dots, P'_{l,m}),$$

where α_m is a **an-arbitrary** weighting factor for the m^{th} association.

69. (Previously presented) The associative memory device of Claim 43, wherein the association function f corresponds to the mathematical operation of multiplication such that two propagated input patterns $P'_i = \psi_m$ and $P'_j = \phi_m$ are associated by multiplying the complex amplitudes of the two wave functions, point by point, at each location r_C in the cortex, with the association represented mathematically as:

$$\psi_m(r_C) \phi_m(r_C)$$

and with all associations previously stored, C , written as the linear combination of associations:

$$C(r_C) = \sum_m \alpha_m \psi_m(r_C) \phi_m(r_C).$$

70. (Previously presented) The associative memory device of Claim 69, wherein the association function f corresponds to the mathematical operation of multiplication of wave fields, one or more of which may be point-wise normalized, the rest non-normalized, such that two propagated input patterns $P'_i = \psi_m$ and $P'_j = \phi_m$ are associated by multiplying the point-wise complex

amplitudes of the two wave functions, at each location r_c in the cortex with the association represented mathematically as:

$$\exp[i \text{Arg}(\psi(r_c))] \exp[i \text{Arg}(\phi(r_c))]$$

or

$$\psi(r_c) \exp[i \text{Arg}(\phi(r_c))]$$

where $\text{Arg}(z)$ is the phase angle for a complex value z , and with all associations previously stored written as the linear combination of associations:

$$C(r_c) = \sum_m \alpha_m \exp[i \text{Arg}(\psi_m(r_c))] \exp[i \text{Arg}(\phi_m(r_c))]$$

or

$$C(r_c) = \sum_m \alpha_m \psi_m(r_c) \exp[i \text{Arg}(\phi_m(r_c))]$$

71. (Currently amended) The associative memory device of Claim 43, wherein the implementation of the associative memory device is mathematically modeled with the wave-modeled prompt on the input buffer being denoted by:

$$R_i, R_j, \dots, R_l;$$

the respective propagated forms of the wave-modeled prompt on the cortex being denoted by:

$$R'_i, R'_j, \dots, R'_l,$$

the wave-modeled prompt being operable to probe the plurality of previously stored associations using f^{-1} , the inverse of the function used originally to form the associations; and the resulting de-associated wave \dot{D} being denoted by:

$$\dot{D} = \langle C | R'_i, R'_j, \dots, R'_l \rangle = f^{-1}(C | R'_i, R'_j, \dots, R'_l) = f^{-1}(\sum_m \alpha_m f(\dot{P}_{i,m}, \dot{P}_{j,m}, \dots, \dot{P}_{l,m}) | R'_i, R'_j, \dots, R'_l);$$

where α_m is a ~~an arbitrary~~ weighting factor for the m^{th} association, a de-association is denoted by angle brackets with a vertical bar separating the first argument, the entity being probed, from the second argument, the set of one or more prompting fields; and D represents the retrieval formed when the complex conjugate of the de-association (\dot{D}^*) is propagated from the cortex to the output buffer.

72. (Previously presented) The associative memory device of Claim 71 further comprising multiplication for the association operation, and the inverse function, f^{-1} , division for the retrieval operation, wherein if a wave field ϕ_n is used to probe the previously stored associated pairs in the cortex, then the retrieval process is denoted by:

$$C\phi_n = \sum_m \alpha_m \psi_m \phi_m \mathbf{I} \phi_n = \sum_m \alpha_m \psi_m \phi_m \phi_n^{-1} = \alpha_n \psi_n + \sum_{m \neq n} \alpha_m \psi_m \phi_m \phi_n^{-1},$$

further, given that the inverse operator \mathbf{I} corresponds to division, the retrieval process is more specifically denoted by:

$$C\phi_n = \sum_m \frac{\alpha_m \psi_m \phi_m}{\phi_n} = \alpha_n \psi_n + \sum_{m \neq n} \frac{\alpha_m \psi_m \phi_m}{\phi_n}$$

where \mathbf{C} contains the linear combination of previously stored associations, and, at each point on the cortex r_c on which \mathbf{C} is defined, the value of \mathbf{C} is divided by the value of ϕ_n , with the retrieval, $\alpha_n \psi_n$, being propagated to the output buffer and then to the output device.

73. (Previously presented) The associative memory device of Claim 72, further comprising:

a retrieval operation, corresponding to the association operation, using complex conjugation as the inverse function f^{-1} , such that if the point-wise normalized wave field ϕ_n is used to probe the previously stored associated pairs in the cortex;

the probe process being denoted by:

$$\begin{aligned} C\phi_n &= \sum_m \alpha_m \exp[i\text{Arg}(\psi_m)] \exp[i\text{Arg}(\phi_m)] \mathbf{I} \exp[i\text{Arg}(\phi_n)] \\ &= \sum_m \alpha_m \exp[i\text{Arg}(\psi_m)] \exp[i\text{Arg}(\phi_m)] \exp[i\text{Arg}(\phi_n)]^{-1} \end{aligned}$$

or

$$C\phi_n = \sum_m \alpha_m \psi_m \exp[i\text{Arg}(\phi_m)] \mathbf{I} \exp[i\text{Arg}(\phi_n)] = \sum_m \alpha_m \psi_m \exp[i\text{Arg}(\phi_m)] \exp[i\text{Arg}(\phi_n)]^{-1}$$

further, given that the inverse operator \mathbf{I} , which embodies the inverse function f^{-1} , corresponds to complex conjugation, the probe process more specifically by:

$$\begin{aligned} C\phi_n &= \sum_m \alpha_m \exp[i\text{Arg}(\psi_m)] \exp[i\text{Arg}(\phi_m)] \exp[-i\text{Arg}(\phi_n)] \\ &= \alpha_n \exp[i\text{Arg}(\psi_n)] + \sum_{m \neq n} \alpha_m \exp[i(\text{Arg}(\psi_m) + \text{Arg}(\phi_m) - \text{Arg}(\phi_n))] \end{aligned}$$

or

$$\begin{aligned} C\phi_n &= \sum_m \alpha_m \psi_m \exp[i\text{Arg}(\phi_m)] \exp[-i\text{Arg}(\phi_n)] \\ &= \alpha_n \psi_n + \sum_{m \neq n} \alpha_m \psi_m \exp(i[\text{Arg}(\phi_m) - \text{Arg}(\phi_n)]) \end{aligned}$$

where C contains the linear combination of previously stored associations, and, at each point r_c on the cortex on which C is defined, the value of C is multiplied by the complex conjugate of the exponential of the phase angle of the prompt ϕ_n , with the retrieval being propagated to the output buffer and to the output device.

74. (Currently amended) A method of autonomous pattern recognition, comprising:
 - sensing physical or electronic stimuli with a sensor;
 - interfacing the output of the sensor to one or a plurality of input buffers;
 - converting the sensed physical or electronic stimuli at the input buffer into wave-modeled input data in the form of complex-valued wave fields;
 - contemporaneously pre-processing the input information and assigning phase values at the input buffer;
 - generating a unique internal identification pattern (IIP) based on a unique identification code assigned automatically or by a system operator to each specific set of input data;
 - storing the IIP in one or more IIP buffers;
 - linking each specific IIP to ~~arbitrary~~ sets of information such as data files to be recalled, sets of commands to be executed or communicated upon a positive identification, and threshold confidence levels required for execution of each particular command or sets of commands;
 - using wave propagation to transport the wave-modeled input data and IIPs from their respective buffers to one or a plurality of recording structures, referred to as a cortex;
 - associating the desired sets of wave-modeled input data and their respective IIPs through an invertible mathematical function or operation, thus creating one or more associations within the cortex;
 - retaining the associations in a distributed manner across the cortex;
 - creating and storing ~~arbitrary~~ linear combinations of associations;
 - inputting prompting data into the input buffer;

converting the prompting data at the input buffer into complex-valued wave fields as wave-modeled prompting data;

contemporaneously pre-processing the prompting data and assigning phase values;

using wave propagation to transport the wave-modeled prompting data to the cortex to prompt a response from the cortex;

mathematically operating upon the previously stored associations at the cortex using a de-association function that is the inverse of that originally used to form the associations;

propagating the result of the mathematical de-association operation; representing a retrieval, to one or more IIP buffers;

autonomously reading a retrieved pattern as accurately as possible;

deducing an identification code that could correspond to a previously created IIP;

generating a confidence estimate based on a relative certainty or uncertainty of the identification made;

recalling the associated files or other information related to the reported identification code and displaying the results in human or machine-readable form;

executing or communicating the appropriate commands based on the identification code, the reported confidence estimate, and the predefined confidence levels required for the relevant commands;

adaptively improving identification performance in response to feedback on the accuracy of past identifications, using the following equation for the case of false positive identifications:

$$C_{\text{new}} = C_{\text{old}} - \beta_i \langle R_i, I_j \rangle$$

where C_{old} is the original cortex value, C_{new} is the revised cortex value, β_i is a positive weighting factor, R_i is the prompting pattern, and I_j is the incorrectly retrieved IIP and using the following equation for the case of false negative or overly weak positive identifications:

$$C_{\text{new}} = C_{\text{old}} + \beta_i \langle R_i - \gamma_i P_i, I_i \rangle$$

where C_{old} is the original cortex value, C_{new} is the revised cortex value, β_i is a positive weighting factor, R_i is the prompting pattern, I_i is the desired IIP, P_i is the original pattern associated with I_i , and γ_i is 0 for augmentation mode and 1 for replacement mode.

75. (Previously presented) The method of autonomous pattern recognition of Claim 74, wherein the method of information transport is by propagating physical waves using antenna arrays and supporting hardware and software.

76. (Currently amended) The method of autonomous pattern recognition of Claim 75, wherein the method of information transport is by simulating wave propagation in computer hardware configured by computer software or wave propagation circuitry in which sets of data are input, pre-processed, and then represented as wave functions $\xi_i(\mathbf{r})$ that are time-harmonic solutions to the wave equation:

$$(\nabla^2 + k^2)\xi_i(\mathbf{r}) = 0;$$

in which the propagation of a wave away from a surface such as a buffer or the cortex is formally and exactly described by the Kirchhoff integral:

$$\xi_i(\mathbf{r}) = \oint_{S_C} d\mathbf{S}_C \cdot \{ \xi_i(\mathbf{r}_C) \nabla_C G(\mathbf{r}, \mathbf{r}_C) - G(\mathbf{r}, \mathbf{r}_C) \nabla_C \xi_i(\mathbf{r}_C) \}$$

where the surface S_C is closed and completely surrounds ~~a the arbitrary~~ destination point \mathbf{r} , the gradient operates only on coordinates on the source surface S_C , and $G(\mathbf{r}, \mathbf{r}_C)$ is a Green's function; and in which the above continuous integral is discretized for numerical implementation as:

$$\xi(\mathbf{r}) = \sum_{\text{all source points}} \Delta S_C \cdot \{ \xi(\mathbf{r}_C) \nabla_C G(\mathbf{r}, \mathbf{r}_C) - G(\mathbf{r}, \mathbf{r}_C) \nabla_C \xi(\mathbf{r}_C) \}$$

thus enabling digital input, output, and computation.

77. (Previously presented) The method of autonomous pattern recognition of Claim 75, wherein the patterns recognized represent physical or electronic stimuli.

78. (Previously presented) The method of autonomous pattern recognition of Claim 77, wherein the physical or electronic stimuli represent images, human faces, sounds, fingerprints, signatures, gas molecules, or chemical compositions.